

BULBRITE
COMPACT FLUORESCENT GU24 BASE
Dimmer Compatibility List

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

13W CFL GU24

Model: CF13WW/GU24/DM

	Manufacturer	Model Number	Overall Results	Lamps per Dimmer	
				Min	Max
Incandescent/Halogen	Legrand	CD703-PW	Pass	1	10
		D703-PTC	Pass	1	10
	Leviton	IPI-06	Pass	1	10
		6633P	Pass	1	10
		Lutron	TG600-PR (AY-600)	Pass	1
	S-600P		Pass	1	10
			DV-600PR	Pass	1
CFL/LED Dimmers	Legrand	DCL453-PTC	Pass	1	10
	Lutron	TGCL-153PH	Pass	1	10
		DVCL-153PL	Pass	1	10
Electronic Low Voltage	Legrand	SCELV	Pass	1	10
	Leviton	VPE04	Pass	1	10
Magnetic Low Voltage	Legrand	DLV703-PW	Pass	1	10
Universal	Legrand	DRD4-W	Pass	1	10

For additional information on the dimmer model of your choice, contact the dimmer manufacturer.

Dimming Range Adjustment for Lutron C•L dimmers

1. Turn dimmer on and **move slider down to the bottom.**
2. Turn adjustment dial **up** (clockwise) until lowest light level is achieved and light output is stable for all bulbs. **Note:** If dial stops, do not continue to turn.
3. Turn dimmer off, then back on to verify bulbs turn on.
4. If all bulbs do not turn on, turn adjustment dial down (counter-clockwise) slightly and repeat step 3.
5. Once all bulbs are dimming properly, install faceplate.

Contact Information:
 Bulbrite Industries Inc.
 145 W. Commercial Ave.
 Moonachie, NJ 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708

©2012 Bulbrite Industries Inc.
 All Rights Reserved.
www.bulbrite.com

BULBRITE
COMPACT FLUORESCENT GU24 BASE
Dimmer Compatibility List

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

18W CFL GU24

Model: CF18WW/GU24/DM

	Manufacturer	Model Number	Overall Results	Lamps per Dimmer	
				Min	Max
Incandescent/Halogen	Legrand	CD703-PW	Pass	1	6
		D703-PTC	Pass	1	6
	Leviton	IPI-06	Pass	1	6
		6633P	Pass	1	6
	Lutron	TG600-PR (AY-600)	Pass	1	6
		S-600P	Pass	1	6
		DV-600PR	Pass	1	6
CFL/LED Dimmers	Legrand	DCL453-PTC	Pass	1	6
	Lutron	TGCL-153PH	Pass	1	6
		DVCL-153PL	Pass	1	6
Electronic Low Voltage	Legrand	SCELV	Pass	1	6
	Leviton	VPE04	Pass	1	6
Magnetic Low Voltage	Legrand	DLV703-PW	Pass	1	6
Universal	Legrand	DRD4-W	Pass	1	6

For additional information on the dimmer model of your choice, contact the dimmer manufacturer.

Dimming Range Adjustment for Lutron C•L dimmers

1. Turn dimmer on and **move slider down to the bottom.**
2. Turn adjustment dial **up** (clockwise) until lowest light level is achieved and light output is stable for all bulbs. **Note:** If dial stops, do not continue to turn.
3. Turn dimmer off, then back on to verify bulbs turn on.
4. If all bulbs do not turn on, turn adjustment dial down (counter-clockwise) slightly and repeat step 3.
5. Once all bulbs are dimming properly, install faceplate.

Contact Information:

Bulbrite Industries Inc.
 145 W. Commercial Ave.
 Moonachie, NJ 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708

©2012 Bulbrite Industries Inc.

All Rights Reserved.

www.bulbrite.com

BULBRITE
COMPACT FLUORESCENT GU24 BASE
Dimmer Compatibility List

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

23W CFL GU24

Model: CF23WW/GU24/DM

	Manufacturer	Model Number	Overall Results	Lamps per Dimmer	
				Min	Max
Incandescent/Halogen	Legrand	CD703-PW	Pass	1	6
		D703-PTC	Pass	1	6
	Leviton	IPI-06	Pass	1	6
	Lutron	TG600-PR (AY-600)	Pass	1	6
		S-600P	Pass	1	6
		DV-600PR	Pass	1	6
CFL/LED Dimmers	Legrand	DCL453-PTC	Pass	1	6
	Lutron	TGCL-153PH	Pass	1	6
		DVCL-153PL	Pass	1	6
Electronic Low Voltage	Legrand	SCELV	Pass	1	6
	Leviton	VPE04	Pass	1	6
Magnetic Low Voltage	Legrand	DLV703-PW	Pass	1	6
Universal	Legrand	DRD4-W	Pass	1	6

For additional information on the dimmer model of your choice, contact the dimmer manufacturer.

Dimming Range Adjustment for Lutron C•L dimmers

1. Turn dimmer on and **move slider down to the bottom.**
2. Turn adjustment dial **up** (clockwise) until lowest light level is achieved and light output is stable for all bulbs. **Note:** If dial stops, do not continue to turn.
3. Turn dimmer off, then back on to verify bulbs turn on.
4. If all bulbs do not turn on, turn adjustment dial down (counter-clockwise) slightly and repeat step 3.
5. Once all bulbs are dimming properly, install faceplate.

Contact Information:

Bulbrite Industries Inc.
 145 W. Commercial Ave.
 Moonachie, NJ 07074
 PHONE: 1-800-528-5555
 FAX: 1-800-441-7708

©2012 Bulbrite Industries Inc.

All Rights Reserved.

www.bulbrite.com